

Wireless sensor
Pull switch FZS65



Only skilled electricians may install this electrical equipment otherwise there is the risk of fire or electric shock!

Temperature at mounting location:
-20°C up to +50°C.
Storage temperature: -25°C up to +70°C.
Relative humidity:
annual average value <75%.

Wireless pull switch for surface mounting 84x84x24 mm or mounting into the E-design switching system*. With grey and red handle.

When the handle is pulled and released, a wireless telegram is sent to the Eltako wireless network.

The scope of supply includes the completely assembled pull switch, an unprinted grey handle, a white printed red handle and two screws and rawl plugs.

Fitting

First dismantle the fully assembled pull switch. To do this, remove the screw, unhook the cover and remove the intermediate frame together with the rocker and transmitter module by loosening the retaining bars at the top and bottom.

Fit the mounting plate by tightening the screws. Engage the frame together with the hook-in cut-outs at the top and the intermediate frame including the transmitter module and rocker with the rear ID O upwards. Insert the cover with the inserted cord into the top hook-in cut-outs of the frame and screw tight into the retaining plate using the screw at the bottom. Shorten the cord to the required length, push it through the red or grey handle and secure it by a double knot.

Independent of position


The pull switch functions in any position, even when attached to the ceiling.

Matching actuators

The wireless pull switch transmits the same wireless telegrams when operated as a wireless pushbutton and can therefore be taught-in in actuators and the GFVS software in the same way. If it will be taught-in in an actuator as 'central on' as an emergency call switch the emergency can only be received with another taught-in switch with 'central off'.

For display we recommend the universal display FUA55LED with 10 LEDs.

* If required, please order an R2E 2-gang or an R3E 3-gang frames with suspension cut-outs.

The wireless module integrated in the wireless pull switch can be taught-in encrypted as described in the operating instructions in all encryptable actuators of the Series 61 and FAM14. This requires the FTVW wireless pushbutton encryption rocker. Encryptable actuators bear the pictogram .

Teaching-in wireless sensors in wireless actuators

All sensors must be taught-in in the actuators so that they can detect and execute commands.

The teach-in process is described in the operation manual of the actuators.


ELTAKO GmbH hereby declares that the products that relates to this operating manual, are in compliance with the essential requirements and other relevant provisions of directive 1999/5/EC.

A copy of the EU declaration of conformity can be requested at the address below.

Must be kept for later use!

Eltako GmbH

D-70736 Fellbach

 +49 711 94350000

www.eltako.com